



## 108\*3W LED MOVING HEAD LIGHT SO108

### POWER SUPPLIES

110V/240V 50/60Hz

### LAMPS SOURCE

Brand:CREE

LED: 3W RGBW \*108pcs

Rated Power:350w

Average Life:100,000hours

### OPTICS

Lens: New Pearl lens

Beam angle: 15°/25°/45°

### EFFECTS SECTION

Color: RGBW color mixing

Strobe: 0.5-20 times/second, adjustment speed

Dimmer: 0-100% linear adjustment

### CONTROL AND PROGRAMMING

DMX:14CH

DMX Control signal: DMX512

DMX Signal Connection: 3pole or 5pole XLR input and output

Other Control: Master/slave, Auto, Voice control

Display:LCD Display

### BODY

Two side handles for transportation

Device locking PAN and TILT mechanisms for transportation and maintenance

### HEAD MOVEMENT

PAN 540°(16bit) electric correction

TILT 270°(16bit) electric correction

With auto-correction function

### ELECTRONICS

Reset from the lighting desk

Built-in overheating and high voltage protection

### ACCESSORIES

DMX Cable: 1pcs

Power Cable: 1pcs

Quick lock system

### CERTIFICATION

CE

RoHS

### PACKING

Light Measurement 44.5 × 31 × 43.5cm

N.W 9KG

With Carton Box: 1 light each carton box

Measurement 46 × 33.5 × 38.5cm

G.W 12KG

With Flight Case: 6 lights each flight case

Measurement 118 × 52 × 73cm

G.W 100KG

### DMX CHANNEL

CH1: Dimmer

CH2: Red color

CH3: Green color

CH4: Blue color

CH5: White color

CH6: Function

CH7: Color mixing effect

CH8: Blank

CH9: PAN

CH10: PAN fine

CH11: TILT

CH12: TILT fine

CH13: Blank

CH14: Reset

